



HD05R Remote Control

The EnVision HD05R remote controls IR-enabled fixtures with integrated sensors. The remote allows modifications to the settings of the sensors. This remote is compatible with the EnVision HD line of sensors.



Remote Keys	Keys Function	Keys Introduction
	ON/OFF	Switch ON/OFF the light; Switch OFF the sensor function.
	MW/PIR	Mode Switch
	Reset	Switch to sensor mode and recover all settings to be factory default setting (Detection area 100%, Hold time 5s, Daylight - Disable Stand-by period 0s, Stand-by dimming level 10%
	Start	Press the key to start the setting of parameters with memory and apply function under the sensor mode. 1 Press "START", the letter "S" will flash in the lower left corner of the display, then start to set up all parameter. 2 After setting all parameters, press "MEMORY" to store settings and keep until the next reset. 3 Press "APPLY" to set the sensor with stored settings within the remote IR range 4 Note: All data shown in the display are the settings after pressing "MEMORY"
	Memory	
	Apply	
	Detection Area	
	Hold Time	Under sensor mode, press the key, the icon on the display flashes, press "+" / "-" to select the hold time. HD06VCRH 782: 5s/30s/1min/3min/5min/10min/20min/30min HD015VCRH: 5s/30s/1min/3min/5min/10min/20min/30min HB001VCR 1: 10s/1min/5min/10min HB002VCR: 5s/30s/1min/3min/5min/10min/20min/30min
	Daylight Threshold	Under sensor mode, press the key, the corresponding icon on the display flashes, press "+" / "-" to select the daylight threshold
	Stand-by Period	Under sensor mode, press the key, the corresponding icon on the display flashes, press "+" / "-" to select the low brightness time. HD06VCRH 782: 0s/10s/30s/1min/5min/10min/30min/60min + ∞ HD015VCRH: 0s/10s/30s/1min/5min/10min/30min + ∞ HB001VCR 1: 1min/30min/60min + ∞ HB002VCR: 0s/10s/30s/1min/5min/10min/30min/60min + ∞
	Stand-by Dimming Level	Under sensor mode, press the key, the corresponding icon on the display flashes, press "+" / "-" to select the brightness during stand-by period

Series HD05R

Optional Accessories (Order Separately) Compatible Sensors

- HD406VRH-D-WH**
Bi Level Motion Sensor w/ Daylight
- HD407V-CR**
Bi-Level Motion Sensor with Daylight
- HD016VCR-8**
Bi-Level Motion Sensor with Daylight