

Round Scoop Downlight Installation Instructions

INSTALLATION INSTRUCTIONS

WARNING: Risk of shock. An electric current can cause painful shock or serious injury unless handled properly. For your safety, always remember to turn OFF power supply at the fuse or circuit breaker box before you install the fixture and ground the fixture to avoid potential electric shock.

WARNING: Risk of cuts. Some metal parts in the fixture may have sharp edges. To prevent cuts and scrapes, wear gloves when handling the parts.

WARNING: This equipment is intended to be installed only by a qualified person. The installation must be made in accordance with the current edition to the National Electric Code and all applicable state and local building codes. The final installation must be approved by the appropriate qualified electrical/building inspectors). Improper installation may result in a fire or electrical hazard. Be sure the electrical power to the circuit has been disconnected before installation.

TOOLS REQUIRED:

- Saw
- Measuring Tape
- Electrical Wiring (Use type and gauge suitable for application to connect the fixtures).

NEW CONSTRUCTION INSTALLATION:

1. Turn OFF the power from the electrical panel before starting installation
2. Secure new construction plate by screwing to joist.
Adjust the new construction plate to the desired location (Fig.1)
3. Install the mounting surface and cut a 4 3/8" diameter hole.
4. Run power supply leads through the mounting hole.
Use NMD90 or BX cable.

REMODEL INSTALLATION:

1. Turn OFF the power from the electrical panel before starting installation
2. Locate a suitable position to install the fixture and cut a 4 3/8" diameter hole in the ceiling.
3. Run power supply leads through the mounting hole.
Use NMD90 or Bx cable.

FIXTURE INSTALLATION:

1. Connect the fixture to the junction box by inserting and twisting the male/female connectors. (Fig. 4)
2. Push spring loaded clips on the fixture upwards and insert fixture base into the mounting hole. Release the clips and fixture will be pulled flush to the ceiling (Fig. 5)
3. Once assembly is complete, turn ON the power to confirm fixture is working properly.

FIXTURE INSTALLATION:

1. Connect the fixture to the junction box by inserting and twisting the male/female connectors. (Fig. 4)
2. Push spring loaded clips on the fixture upwards and insert fixture base into the mounting hole. Release the clips and fixture will be pulled flush to the ceiling (Fig. 5)
3. Once assembly is complete, turn ON the power to confirm fixture is working properly.

REPLACE OPTIC AND/OR TRIM:

1. Turn OFF power from the electrical panel. If installed, remove from ceiling.
2. To replace optic, turn cap counter clockwise to unlock and replace (Fig. 6)
3. To replace trim, turn counter clockwise to unlock and replace (Fig. 6)
4. Connect the fixture to the junction box by inserting and twisting the male/female connectors (Fig. 4)
5. Reinstall fixture and turn ON power to confirm fixture is working properly (Fig. 5)

